

# ORBIT 60 SERIES Relay Modules

## Datasheet

Bently Nevada Machinery Condition Monitoring

137M0699 Rev. A

### Description

Program Relay modules to actuate based on alarm conditions defined in other modules. Use standard logic elements (True AND, Normal AND, OR and NOT) to combine various alarms and statuses (alarm statuses, OK statuses and other statuses (Bypass, Protection State, Inhibit, Attention, Protection Fault, etc.) into relay activation conditions. Use Orbit Studio to program the voting logic.

Relays can operate as a system or group protection fault relay, if programmed to do so, especially when the protection fault relay on the SIM does not provide adequate granularity of system health - typically for multiple machines in one system.

Pairs of relays within the module function as a single Double-Pole, Double-Throw relay when appropriately configured. All relay types are available for SIL system implementation.



### Electromechanical Relay (EMR)

This relay drives a load directly, or through, an interposing relay. This module takes two slots. It features **8 Epoxy Sealed, Single-Pole Double-Throw Electromechanical Relays**. This module supports an AC voltage range of 5-250 Vac for loads of 100 mA to 4 A. The module also supports DC voltages and loads of 5-30 Vdc at 4 A.

### Solid State Relay (SSR)

This relay connects to an external system's discrete input for low current communication. It occupies a single slot and features **8 Solid-State Relays**. This module supports secondary voltages from 1 Vdc up to 125 Vdc and loads of 0.01-125 mA.



## Electromagnetic Relay (EMR)

Electromagnetic Relay (EMR)	
Power Consumption	
Typical	6 watts
Maximum	11 watts
Characteristics	
Type	Electromechanical Single-Pole, Double-Throw
Number of Relay Outputs	8
Environmental	Epoxy Sealed
Arc Suppressor	250 Vrms, installed standard
Contact Life	100,000 cycles @ 5 A, 24 Vdc or 240 Vac
Operation	Each relay is configurable for Normally De-Energized or Normally Energized
Contact Rating for Standard Systems	
Minimum Switched Current	100 mA
DC Maximum Switched Current	4 A @ 30 Vdc
DC Minimum Switched Voltage	5 Vdc
DC Maximum Switched Voltage	30 Vdc
AC Maximum Switched Voltage	250 Vrms
AC Maximum Switched Current	4 A
Maximum Switched Power	180 W or 1800 VA

Electromagnetic Relay (EMR)	
Contact Rating for Hazardous Area Systems	
Maximum Switched Current	4 A
DC Maximum Switched Voltage	30 Vdc
AC Maximum Switched Voltage	160 Vrms

## Solid State Relay (SSR)

Solid State Relay (SSR)	
Power Consumption	
Typical	5 watts
Maximum	9 watts
Characteristics	
Type	Solid State Single-Pole, Double-Throw
Number of Relay Outputs	8
Environmental	Plastic Encapsulated
Arc Suppressor	150 Vdc, installed standard
Maximum Cycling Rate	1 Hz
Operation	Each relay is configurable for Normally De-Energized or Normally Energized
Switching Properties	Limited to non-inductive loads
Contact Rating for Standard Systems	
Current Range	0.0 I-125 mA
DC Maximum Switched Current	125 mA @ 125 Vdc

### Solid State Relay (SSR)

Voltage Range	1-125 Vdc
Maximum Switched Power	650 mW
Contact Rating for Hazardous Area Systems	
Current Range	0.0 1-125 mA
Voltage Range	1-50 Vdc

## Compliance and Certifications

### FCC

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- This device may not cause harmful interference.
- This device must accept any interference received, including interference that may cause undesired operation.

### EMC

European Community Directive:  
EMC Directive 2014/30/EU

Standards:

EN 61000-6-2; Immunity for Industrial Environments  
EN 61000-6-4; Emissions for Industrial Environments

### Electrical Safety

European Community Directive:  
LV Directive 2014/35/EU

Standards:

EN 61010-1;  
EN 61010-2-201;

### RoHS

European Community Directive:  
RoHS Directive 2011/65/EU

### Cyber Security

Designed to meet IEC 62443-4-2

### \*Maritime

ABS Rules for Condition of Classification, Part 1

- Steel Vessels Rules
- Offshore Units and Structures

\* Approvals pending

### Functional Safety

For SIL 2 compliance, two relay modules must be ordered and installed to act redundantly.

### Hazardous Area Approvals



For the detailed listing of country and product-specific approvals, refer to the [Approvals Quick Reference Guide \(108M1756\)](#).

For additional technical documentation, please log in to [bntechsupport.com](http://bntechsupport.com) and access the Bently Nevada Media Library.

### cNRTLus

Class I, Zone 2: AEx/Ex ec nC IIC T4 Gc;  
Class I, Zone 2: AEx/Ex nA nC IIC T4 Gc;  
Class I, Division 2, Groups A, B, C, D T4;  
Class I, Division 2, Groups A, B, C, D T4 (N.I.);

T4 @ Ta= -30°C to +70°C (-22°F to +158°F)

### ATEX/IECEx



Ex II 3 G  
Ex ec nC IIC T4 Gc  
Ex nA nC IIC T4 Gc

T4 @ Ta= -30°C to +70°C (-22°F to +158°F)

## Ordering Information



For the detailed listing of country and product-specific approvals, refer to the [Approvals Quick Reference Guide \(108MI756\)](#).

For additional technical documentation, please log in to [bntechsupport.com](http://bntechsupport.com) and access the Bently Nevada Media Library.

## Electromechanical Relay Module

Ordering Option	Description
60R/RLY01-AAA-B	
AAA – Hazardous Area Certifications	
00	No Hazardous Area
01	CSA/NRTL/C (Class I, Div 2)
02	Multi (CSA, ATEX, IECEx)
XXX	Country Specific Approvals
B – SIL Level	
0	No SIL
1	SIL 1

## Solid State Relay Module

Ordering Option	Description
60R/RLY02-AAA-B	
AAA – Hazardous Area Certifications	
00	No Hazardous Area
01	CSA/NRTL/C (Class I, Div 2)
02	Multi (CSA, ATEX, IECEx)
XXX	Country Specific Approvals
B – SIL Level	
0	No SIL
1	SIL 1

Copyright 2023 Baker Hughes Company. All rights reserved.



Bently Nevada and Orbit Logo are registered trademarks of Bently Nevada, a Baker Hughes business, in the United States and other countries. The Baker Hughes logo is a trademark of Baker Hughes Company. All other product and company names are trademarks of their respective holders. Use of the trademarks does not imply any affiliation with or endorsement by the respective holders.

Baker Hughes provides this information on an "as is" basis for general information purposes. Baker Hughes does not make any representation as to the accuracy or completeness of the information and makes no warranties of any kind, specific, implied or oral, to the fullest extent permissible by law, including those of merchantability and fitness for a particular purpose or use. Baker Hughes hereby disclaims any and all liability for any direct, indirect, consequential or special damages, claims for lost profits, or third party claims arising from the use of the information, whether a claim is asserted in contract, tort, or otherwise. Baker Hughes reserves the right to make changes in specifications and features shown herein, or discontinue the product described at any time without notice or obligation. Contact your Baker Hughes representative for the most current information.

The information contained in this document is the property of Baker Hughes and its affiliates; and is subject to change without prior notice. It is being supplied as a service to our customers and may not be altered or its content repackaged without the express written consent of Baker Hughes. This product or associated products may be covered by one or more patents. See [Bentley.com/legal](https://www.bentley.com/legal).

1631 Bently Parkway South, Minden, Nevada USA 89423  
Phone: 1.775.782.3611 (US) or [Bentley.com/support](https://www.bentley.com/support)  
[Bentley.com](https://www.bentley.com)