

10MHz REFERENCE

Level : 12dbm +/- 2dbm into 50ohms
 Harmonics : <-50dbc
 Accuracy : 1×10^{-12} Long term

Short Term Stability

tau	Allan Variance (typ)
1s	2×10^{-12}
10s	$< 4 \times 10^{-13}$
100s	$< 5 \times 10^{-12}$
1000s	$< 2 \times 10^{-12}$

Phase noise (typ)

1Hz	-110dbc
10Hz	-136dbc
100Hz	-145dbc
1kHz	-155dbc
10kHz	-157dbc

Frequency Divider Outputs

1Hz • 2Hz • 5Hz • 10Hz • 20Hz • 50Hz • 100Hz
 200Hz • 500Hz • 1kHz • 2kHz • 10kHz • 20kHz • 50kHz
 100kHz • 200kHz • 500kHz • 1MHz • 2MHz • 5MHz

Level into 1Mohm : 1V pk-pk \pm 50mV Square wave
 Level into 50ohms : 500mV pk-pk \pm 30mV Square wave

Accuracy : 1×10^{-12} Long term

LF MEASURE

Range : 1Hz to 10MHz
 Accuracy : 1×10^{-12} +/- 1 count
 Resolution : 0.01ppm or 1uHz, which ever is greater
 Min input level High Sensitivity : 0.3V
 Low Sensitivity : 200mV
 Gate times : 0.1s, 1s or 10s
 Trigger level : 0 to 2V in 10mV steps
 Period measurement
 HF Filter

HF MEASURE

Accuracy : 1×10^{-12} +/- 1 count
 Resoultion : 10Hz

Min input level : 10MHz to 30MHz (700mV pk to pk)
 30MHz to 100MHz (300mV pk to pk)
 100MHz to 1000MHz (200mV pk to pk)

ORDERING INFORMATION

MODEL 8600 SOURCE / MEASURE GPS FREQUENCY STANDARD (BASE)
 UKAS 8600 UKAS CERTIFICATION

INTERNAL OPTIONS OPTION GPS GPS REFERENCE MODULE
 OPTION RUBIDIUM RUBIDIUM REFERENCE MODULE

VARIABLE FREQUENCY AND LEVEL OUTPUT

Sinewave

Frequency : 10Hz to 2MHz (1Hz steps)
 Accuracy : 0.8ppm

Level into 1MOhm

High range Level : 250mV to 5V RMS (10mV steps)
 Accuracy : 2%.

Low range Level : 0mV to 250mV RMS (1mV steps)
 Accuracy : 2% \pm 100uV.

Level into 50Ohms

High range Level : 125mV to 2.50V RMS (5mV steps)
 Accuracy : 2%

Low range Level : 0mV to 125mV RMS (0.5mV steps)
 Accuracy : 2% \pm 100uV.

Square Wave

Frequency : 10Hz to 2MHz (1Hz steps)
 Accuracy : 0.8ppm
 Level : 5V pk-pk \pm 0.5V

HF Output

5MHz to 1.05GHz (100kHz steps)
 Level : 600mV \pm 150mV pk-pk. into 50 Ohms
 Accuracy : 1×10^{-12} Long term

A-B Outputs

Frequency points

1Hz, 2Hz, 5Hz, 10Hz, 20Hz, 50Hz, 100Hz, 200Hz,
 500Hz, 1000Hz, 2000Hz, 5000Hz

Level into 1 MOhm : 1V pk-pk \pm 50mV Square wave

Level into 50 Ohms : 500mV pk-pk \pm 30mV Square wave

Phase range 0 to 359° (1° steps)

Phase accuracy : 0.0000072° x Frequency (in Hz)

ADVANCED GPS FREQUENCY STANDARD



8600 SPECIFICATIONS



UNIT 4 SELECT BUSINESS CENTRE,
 LODGE ROAD, STAPLEHURST, KENT.
 TN12 0QW, UNITED KINGDOM.
 TEL : +44 (0) 1580 890700
 FAX : +44 (0) 1580 890711
 EMAIL : sales@transmille.com
WWW.TRANSMILLE.COM

AGENT

Due to continuous development specifications are subject to change
 Windows is a registered trademark of Microsoft Corporation
 All other product names mentioned herein may be trademarks of their respective companies.

V1.00

8600 SERIES

FREQUENCY SOURCE / MEASURE
GPS STANDARD



8600 SERIES FREQUENCY SOURCE / MEASURE GPS STANDARD

TRANSMILLE
SOLUTIONS IN CALIBRATION


DUAL DISPLAY TECHNOLOGY



INTELLIGENT DATA DISPLAY


MULTI INTERFACE SUPPORT



FOR FLEXIBLE SYSTEMS INTEGRATION


INTEGRATED GPS REFERENCE TECHNOLOGY



FOR ULTRA PRECISION


MULTI PROCESSOR TECHNOLOGY



FOR ADVANCED FUNCTIONALITY



FUNCTIONS AT A GLANCE

FREQ SOURCE SOURCE TO 1GHz

FREQ MEASURE MEASUREMENT TO 1GHz

GPS INTEGRATED GPS REFERENCE

PHASE TIME USER CONFIGURABLE PHASE / TIME DELAY

O/P x3 3 SOURCE MODE OUTPUTS

I/P x2 2 MEASURE MODE INPUTS

DUAL VFD DUAL VACUUM FLUORESCENT DISPLAYS

OVERVIEW

The innovative 8600 Frequency Source / Measure GPS Standard features a high accuracy precision GPS referenced frequency output of up to 1GHz, phase/time output.

In addition, the 8600 offers high accuracy measurement functionality up to 1GHz.

Utilising the latest in GPS reference technology the 8600 combines both frequency source and measurement capabilities into one integrated standard.

Dual displays provide the user with a dedicated source/measure readout, with detailed settings and satellite Lock / signal information in a secondary display.

ADVANCED FREQUENCY STANDARD

The 8600 has been designed to be able to calibrate a wide variety of handheld and bench frequency counters and phase meters, with a fully variable output.

Source mode offers three dedicated terminal sets (A • B • HF), and measurement via two terminal sets (LF • HF)

OUTPUT A

A fully variable GPS referenced output of up to 10MHz, a variable output level Up to 5V PK-PK.

OUTPUT B

User configurable phase / time delay with fully variable GPS referenced output of up to 10MHz, a variable output level up to 5V PK-PK.

OUTPUT C

High frequency output offering a dedicated fully variable frequency output from 10MHz up to 1GHz allowing a full range of meters to be calibrated.